

LX0DRR, LX0RU Settings for Brandmeister Network

LX0DRR DMRid TG270102
LX0RU DMRid TG270100

LX0DRR	TS1	TG9	Local
	TS1	TG2701	All LX DMR Relais (ADRAD and RL, Gateway D-Star)
	TS1	TG27062	Gateway D-Star XLX270B, DCS270B
	TS2	TG9	Local
	TS2	TG270102	Gateway to LX0RU TS2
	TS2	TG27058	Interlink LX0DRR, LX0RU TS2
LX0RU	TS1	TG9	Local
	TS1	TG2701	All LX DMR Relais (ADRAD and RL, Gateway D-Star)
	TS1	TG27062	Gateway D-Star XLX270B, DCS270B
	TS2	TG9	Local
	TS2	TG270100	Gateway to LX0DRR TS2
	TS2	TG27058	Interlink LX0DRR, LX0RU TS2

Echo Funktion: Privat call 262997 TS2

Status: Privat call 262994 TS2
Send Text message "RPT" (TYT, etc)
Send Quick text "RPT" (Hytera)

Info any Callsign Privat call 262993 TS2
Send Text message "INFO LXxxx"
(LXxxx = any callsign)

Contacts :

TG2701	Group call - 2701
TG270100	Group call - 270100
TG270102	Group call - 270102
Echo 262997	Privat call - 262997
Status 262994	Privat call - 262994
SMS 262993	Privat call - 262993

RX Group List: TG9,TG8, TG270, TG2701, TG270100, TG270102,
TG9112, TG2705

Don't forget to register at Brandmeister Network !
<https://brandmeister.network/?page=register>